### **Datasheet**

### 8 in 9 out 4K 30Hz HDMI matrix switcher

Model:CH8830K\_B

# **Features**

- Full-featured 8-in 9-out digital audio and video 4K HDMI audio and video signal matrix switcher.
- It can be selected arbitrarily, 1 input, 1 output, 1 input and multiple output or cross selection switching for each channel.
- Supports 4K x 2K @30Hz, 1080P @120Hz, 1080P 3D @60Hz.
- Deep Color supports 48/36/30/24-bit.

**PANIO** 

- Support the 1st output sound separate independent output.
- Support independent manual EDID function for each port.
- Support LPCM 7.1CH, Dolby True HD, Dolby Digital and DTS-HD Master Audio transmission.
- Two-button control method: the first press selects the input device, the second press selects the output port, and supports quick cancellation of the selected port.
- Control method: button, remote control, 3xRS-232, Web UI, mobile phone tablet APP.
- It can store 8 kinds of scenes for use, and quickly recall the saved scene modes without switching operations one by one.
- Radio and television grade switching chip, image switching can be completed with a single chip, and the switching efficiency is higher.
- Chinese and English WEB control interface.
- Support 19" rack size.

Diagram

## **Specification**

Model Name	CH8830K_B
Input	8 x HDMI ( Type A Female )
Output	9 x HDMI ( Type A Female ), 1 x 3.5mm (1st output sound)
Support resolution	480i, 576i, 480p, 576p, 720p ,1080i, 1080p @24/30/50/60/120Hz, 1080P 3D @60Hz, 4K @30Hz
Electrostatic protection	Human body discharge mode: ± 8kV (air-gap discharge) ±4kV (contact discharge)
Control Interface	2 x RS-232 Male, 1 x RS-232 Female, 1 x RJ-45
Protocol standard	Support HDMI1.4b, support EDID management, support HDCP
Length of connecting cable	Input and output can be connected to HDMI cables with a maximum length of 5 meters. If the length exceeds this length, it is recommended to
	use an extender to extend the distance.
Weight	use an extender to extend the distance. 2kg
Weight Control method	
Control method	2kg Button, remote control, 3xRS232, WEB, ios

### **Package contents**

- 1 X CH8830K\_B
- 1 X 12V 2A adapter
- 1 X Remote control (battery not provided)
- 1 X User manual



Diagram