

2 進 2 出 BNC+VGA 轉 HDMI+VGA 切換轉換器

Model:HVB22A

功能特性

- 多介面 2 進 2 出-切換+同步顯示+轉換器.
- 支援 BNC 輸入解析度：
800x600/60/75Hz,1024x768/60Hz,1280x720p/60Hz,1280x1024/60Hz,1360x768/60Hz,1440x900/60Hz,1680x1050/60Hz,1920x1080p/60Hz.
- 支援 VGA 輸入解析度：
800x600/60/75Hz,1024x768/60Hz,1280x720/60Hz,1280x1024/60Hz,1360x768/60Hz,1400x1050/60Hz,1440x900/60Hz,1600x1200/60Hz,1680x1050/60Hz,1920x1200/60Hz,1920x1400/60Hz,1920x1080/60Hz.
- 支援影音同步輸出.
- BNC 輸入支援亮度、對比度、銳度和飽和度調節、畫面暫停功能.

包裝配件

- 1 x 5V 變壓器
- 1 x 操作說明書

產品示意圖

連接示意圖

提供BNC+VGA +Audio 訊號輸入 轉 HDMI + VGA +Audio 訊號輸出，切換分配顯示



規格表

型號	HVB22A		
輸入介面	1×BNC	1xVGA	1×3.5mm
輸出介面	1×HDMI	1xVGA	1×3.5mm
BNC 輸入解析度	800x600/60/75Hz,1024x768/60Hz,1280x720p/60Hz,1280x1024/60Hz,1360x768/60Hz,1440x900/60Hz,1680x1050/60Hz,1920x1080p/60Hz.		
VGA 輸入解析度	800x600/60/75Hz,1024x768/60Hz,1280x720/60Hz,1280x1024/60Hz,1360x768/60Hz,1400x1050/60Hz,1440x900/60Hz,1600x1200/60Hz,1680x1050/60Hz,1920x1200/60Hz,1920x1400/60Hz,1920x1080/60Hz.		
電源供應	AC 110V-240V 50/60HZ DC:5V		